


User Manual



CHAUVET®
Value • Innovation • Performance

It's Green Thinking

TABLE OF CONTENTS

1. BEFORE YOU BEGIN.....	3
WHAT IS INCLUDED	3
UNPACKING INSTRUCTIONS	3
MANUAL CONVENTIONS.....	3
ICONS.....	3
SAFETY INSTRUCTIONS.....	4
2. INTRODUCTION	5
PRODUCT OVERVIEW	5
3. SETUP	6
AC POWER	6
FUSE REPLACEMENT	6
<i>Power Linking.....</i>	<i>7</i>
MOUNTING	8
<i>Orientation.....</i>	<i>8</i>
<i>Rigging.....</i>	<i>8</i>
4. OPERATING INSTRUCTIONS	9
USING THE CONTROL PANEL.....	9
MENU MAP.....	9
CONFIGURING THE STARTING ADDRESS.....	9
OPERATION.....	10
<i>DMX Operation.....</i>	<i>10</i>
<i>DMX Channel Values.....</i>	<i>10</i>
<i>Master/Slave Mode (Auto, Sound active).....</i>	<i>12</i>
STANDALONE.....	12
<i>Sound-Active.....</i>	<i>12</i>
<i>Auto-Selection.....</i>	<i>12</i>
<i>Auto-Configure</i>	<i>13</i>
5. APPENDIX	14
GENERAL TROUBLESHOOTING	14
DMX PRIMER.....	15
FIXTURE LINKING (DAISY CHAIN).....	15
DATA CABLING.....	15
<i>DMX Data Cable.....</i>	<i>15</i>
CABLE CONNECTORS.....	16
SETTING THE STARTING ADDRESS	16
<i>3-Pin to 5-Pin Conversion Chart.....</i>	<i>17</i>
<i>Setting up a DMX Daisy Chain.....</i>	<i>17</i>
GENERAL MAINTENANCE	18
RETURNS PROCEDURE.....	18
CLAIMS.....	18
TECHNICAL SPECIFICATIONS	19
CONTACT US.....	20

CHAUVET®, 2010, All Rights Reserved

Information and specifications in this User Manual are subject to change without notice.

CHAUVET® assumes no responsibility or liability for any errors or inaccuracies that may appear in this manual.

Author: Anthony Chiappone

Revision: 01b

Release Date: 01-17-2011

1. BEFORE YOU BEGIN

What is included

- 1 x Circus™
- 1 x Power Cord
- 1 x Warranty Card
- 1 x User Manual

Unpacking Instructions

Immediately upon receiving a fixture, carefully unpack the carton, check the contents to ensure that all parts are present, and have been received in good condition. Notify the shipper immediately and retain packing material for inspection if any parts appear damaged from shipping or the carton itself shows signs of mishandling. Save the carton and all packing materials. In the event that a fixture must be returned to the factory, it is important that the fixture be returned in the original factory box and packing.




Manual Conventions

CHAUVET® manuals use the following conventions to differentiate certain types of information from the regular text.

CONVENTION	MEANING
[10]	A DIP switch to be configured
<Menu>	A key to be pressed on the fixture's control panel
1~512	A range of values
50/60	A set of values of which only one can be chosen
<i>Settings</i>	A menu option not to be modified (for example, showing the operating mode/current status)
<i>MENU>Settings</i>	A sequence of menu options to be followed
ON	A value to be entered or selected

Icons

This manual uses the following icons to indicate information that requires special attention on the part of the user.

ICONS	MEANING
	This paragraph contains critical installation, configuration or operation information. Failure to comply with this information may render the fixture partially or completely inoperative, cause damage to the fixture or cause harm to the user.
	This paragraph contains important installation or configuration information. Failure to comply with this information may prevent the fixture from functioning correctly.
	This paragraph reminds you of useful, although not critical, information.

Safety Instructions




Please read these instructions carefully. It includes important information about the installation, usage and maintenance of this product.

- Please keep this User Manual for future consultation. If you sell the unit to another user, be sure that they also receive this instruction booklet.
- Always make sure that you are connecting to the proper voltage, and that the line voltage you are connecting to is not higher than that stated on the decal or rear panel of the fixture.
- This product is intended for indoor use only! To prevent risk of fire or shock, do not expose fixture to rain or moisture.
- Make sure there are no flammable materials close to the unit while operating.
- The unit must be installed in a location with adequate ventilation, at least 20in (50cm) from adjacent surfaces. Be sure that no ventilation slots are blocked.
- Always disconnect from power source before servicing or replacing fuse and be sure to replace with same fuse source.
- Secure fixture to fastening device using a safety chain.
- Maximum ambient temperature (Ta) is 104°F (40°C). Do not operate fixture at temperatures higher than this.
- In the event of a serious operating problem, stop using the unit immediately. Never try to repair the unit by yourself. Repairs carried out by unskilled people can lead to damage or malfunction. Please contact the nearest authorized technical assistance center.
- Never connect the device to a dimmer pack.
- Make sure the power cord is never crimped or damaged.
- Never disconnect the power cord by pulling or tugging on the cord.
- Never carry the fixture directly from the cord. Always use the hanging/mounting bracket.
- Avoid direct eye exposure to the light source while it is on.

2. INTRODUCTION

Product Overview



3. SETUP

AC Power

This fixture is auto-ranging and runs on 100~240 VAC, 50/60 Hz power.

To determine the power requirements for a particular fixture, see the label affixed to the back plate of the fixture or refer to the fixture's specifications chart. A fixture's listed current rating indicates its average current draw under normal conditions.



Always connect the fixture to a switched circuit. Never connect the fixture to a rheostat (variable resistor) or dimmer circuit, even if the rheostat or dimmer channel is used only as a 0 to 100% switch.



Always connect the fixture to a circuit with a suitable electrical ground.

Fuse Replacement




Disconnect the power cord before replacing a fuse.



Always replace with the same type & rating fuse!

1. With a flat head screwdriver wedge the fuse holder out of its housing.
2. Remove the damaged fuse from its holder and replace with exact same type fuse.
3. Insert the fuse holder back in its place and reconnect power.





Power Linking

This fixture contains power linking via the Edison outlet located in front of the power input cable.

Please see the diagram below for further explanation.



The maximum quantity of Circus™ fixtures that may be linked is 26 units @ 120V, 40 units @ 230V



The power linking shown in this document is for the CHAUVET® North American version ONLY! Therefore, it is the customer's responsibility to check with the Dealer/Distributor regarding power linking on the local version of the product. Connections and availability may change, depending on the power requirements and/or regulations of each country/region.

Mounting

Orientation

The Circus™ may be mounted in any position, provided there is adequate room for ventilation.


Rigging

Be sure that the structure can support the weight of the fixture. Please see the "Technical Specifications" section of this manual for a detailed weight listing. Mount the fixture securely. This may be done with a screw, nut and bolt, or a mounting clamp.

The hole in each bracket is 13 mm in diameter.

When rigging, consider routine maintenance and control panel access. Please see the following notes on installation.

- If the power link out is intended to be used with multiple fixtures, take into account the length of each power cable, and mount the fixtures close enough to one another to accommodate for this.
- When aiming the fixtures, use the bracket/yoke adjustment knobs. Loosen the knobs, adjust to the desired angle, and then tighten the knobs by turning them clockwise. Do not use tools for this step, as it may cause damage.
- Safety cables must always be used!








4. OPERATING INSTRUCTIONS

Using the Control Panel

Access control panel functions using the four buttons located directly underneath the LED display.

BUTTON	FUNCTION
<MODE>	Used to scroll through the current operating mode, as well as back out of the current menu option
<DOWN>	Used to select a decreasing value
<UP>	Used to select an increasing value
<ENTER>	Used to activate a selection and store it to memory





MODE DOWN UP ENTER

Menu Map

MENU	PROGRAMMING STEPS		Description
DMX address	d.001~512		Select the starting address
Standalone: slave	SLAu		Slave operating mode
Standalone: sound	SOUn		Sound active standalone mode
Microphone sensitivity	SE.00~31		Microphone sensitivity (sound active mode only)
Standalone: static	C.L.r-		Red
	C.L.g-		Green
	C.L.b-		Blue
	C.L.y-		Amber
	C.L.u-		White
Software version	v-#.#		Displays the software version installed
Standalone: auto-selection	Pr.01~42		Operate in standalone mode with preset run speeds
Standalone: auto-configure	AUTO	n000~100	Program progression time (slow~fast)
		SP00~99, FL	Run speed (slow~fast)
		FS00~99	Strobe rate (off, slow~fast)

Configuring the Starting Address

The Circus™ fixture uses **three** DMX channels. In this DMX configuration/personality, the highest configurable address is **510**. Any address higher than this will prevent access to all of the channels while in this mode; however, if you desire to use one of the other DMX configurations (personalities), please consider the total DMX channels when selecting a DMX address.

If this is your first time using DMX, we recommend reading the “DMX Primer” section in the “Appendix”.

Operation

DMX Operation

This operating mode will allow for DMX control. You must set the starting address for this mode.

If this is your first time using DMX, then it is recommended that you refer to the "DMX Primer" section in the "Appendix" of this manual.

Please see the instructions below for details on this mode.

1. Plug the fixture into power.
2. Plug a DMX controller into the fixture in a daisy chain configuration.
3. Press **<MENU>** until **d.001~512** appears on the LED screen.
4. Press **<ENTER>**.
5. Using **<UP>** & **<DOWN>**, select the DMX starting address: d001~512.
6. Press **<ENTER>**.

DMX Channel Values

CHANNEL	FUNCTION	VALUE	SETTING
1	Program/Mode	000 ○ 000	No function
		001 ○ 005	Automatic 1
		006 ○ 011	Automatic 2
		012 ○ 017	Automatic 3
		018 ○ 023	Automatic 4
		024 ○ 029	Automatic 5
		030 ○ 035	Automatic 6
		036 ○ 041	Automatic 7
		042 ○ 047	Automatic 8
		048 ○ 053	Automatic 9
		054 ○ 059	Automatic 10
		060 ○ 065	Automatic 11
		066 ○ 071	Automatic 12
		072 ○ 077	Automatic 13
		078 ○ 083	Automatic 14
		084 ○ 089	Automatic 15
		090 ○ 095	Automatic 16
		096 ○ 101	Automatic 17
		102 ○ 107	Automatic 18
		108 ○ 113	Automatic 19
		114 ○ 119	Automatic 20
		120 ○ 125	Automatic 21
		126 ○ 131	Automatic 22
		132 ○ 137	Automatic 23
		138 ○ 143	Automatic 24
		144 ○ 149	Automatic 25
		150 ○ 155	Automatic 26
		156 ○ 161	Automatic 27
		162 ○ 167	Automatic 28
		168 ○ 173	Automatic 29
		174 ○ 179	Automatic 30
		180 ○ 185	Automatic 31
		186 ○ 191	Automatic 32
		192 ○ 197	Automatic 33
		198 ○ 203	Automatic 34
		204 ○ 209	Automatic 35
		210 ○ 215	Automatic 36
		216 ○ 221	Automatic 37
		222 ○ 227	Automatic 38
		228 ○ 233	Automatic 39
		234 ○ 239	Automatic 40
		240 ○ 245	Automatic 41
		246 ○ 251	Automatic 42
		252 ○ 255	Sound-active

Continues in the next page

Continued from previous page

CHANNEL	FUNCTION	VALUE	SETTING
2	Run Speed (When running programs)	000 ó 255	0~100%
	Sound Sensitivity (When in Sound Active Mode)	000 ó 255	0~100%
3	Strobe Speed (Only for programs)	000 ó 255	0~100%

Master/Slave Mode (Auto, Sound active)

When additional (slave) fixtures are daisy chained to the master, they will all synchronize with the master and run the same lighting show.

Please see the instructions below for details on this mode.

Master:

1. Place the master fixture **first** in the daisy chain.
2. Set the master fixture to operate in either automatic or sound-active mode; *please see the appropriate sections of this manual for details on this procedure.*

Slave:

1. Daisy chain from the output of the master fixture.
2. Press **<MENU>** until **SLAu** appears on the LED screen.
3. Press **<ENTER>**.



Plug the master fixture in LAST!



Only connect a maximum of 31 slave fixtures when operating in this mode!

Standalone

Sound-Active

Please see the instructions below for details on this mode.

1. Plug the fixture into power.
2. Press **<MENU>** until **SOU**n appears on the LED screen.
3. Press **<ENTER>**.
4. Press **<MENU>** until **SE.00~31** appears on the LED screen.
5. Using **<UP>** & **<DOWN>**, adjust the microphone sensitivity (**S_1~S100**).
6. Press **<ENTER>**.



The microphone will only respond to low frequencies (bass).

Auto-Selection

Please see the instructions below for details on this mode.

1. Plug the fixture into power.
2. Press **<MENU>** until **Pr.01~42** appears on the LED screen.
3. Press **<ENTER>**.
4. Using **<UP>** & **<DOWN>**, adjust the desired program.
5. Press **<ENTER>**.



The playback speed is not adjustable in this mode.

Auto-Configure

This fixture has 42 built in light shows. In this mode, the fixture will cycle through each of these programs.

Please see the instructions below for details on this mode.

1. Plug the fixture into power.
2. Press **<MENU>** until **AUTO** appears on the LED screen.
3. Press **<ENTER>** to scroll through the configurable parameters (**n.*****, **SP.****, **SF.****). Stop when you reach **n.*****.
4. Using **<UP>** & **<DOWN>**, adjust the light show progression time between **000~100**. This is the time that the fixture will run a single show before proceeding to the next.
5. Press **<ENTER>** until you reach **SP****.
6. Using **<UP>** & **<DOWN>**, adjust the run speed between **00~99**, **FL**. FL in the menu signifies full run speed.
7. Press **<ENTER>** until you reach **SF****.
8. Using **<UP>** & **<DOWN>**, adjust the strobe speed between **00~99**, **FL**. FL in the menu signifies full strobe speed.
9. Press **<ENTER>**.



n.000~100 is used to modify the light show progression.



SP.00~99, FL is used to modify the run speed.



SF.00~99, FL is used to modify the strobe speed.

5. APPENDIX

General Troubleshooting

SYMPTOM	POSSIBLE CAUSE(S)	POSSIBLE ACTION(S)
Breaker/Fuse keeps blowing	<ul style="list-style-type: none"> Excessive circuit load Short circuit along the power wires 	<ul style="list-style-type: none"> Check total load placed on the electrical circuit Check for a short in the electrical wiring (internal and/or external)
Device does not power up	<ul style="list-style-type: none"> No power Loose power cord 	<ul style="list-style-type: none"> Check for power on Mains Check power cord
Fixture is not responding to DMX	<ul style="list-style-type: none"> Wrong DMX addressing Damaged DMX cables Wrong polarity settings on the controller Loose DMX cables Faulty DMX interface Faulty Main PCB 	<ul style="list-style-type: none"> Check Control Panel and unit addressing Check DMX cables Check polarity switch settings on the controller Check cable connections Replace DMX input Replace Main PCB
Loss of signal	<ul style="list-style-type: none"> Non DMX cables Bouncing signals Long cable / low level signal Too many fixtures Interference from AC wires 	<ul style="list-style-type: none"> Use only DMX compatible cables Install terminator as suggested Install amplifier right after fixture with strong signal. Install an optically coupled DMX splitter after unit #32 Keep DMX cables separated from power cables or black lights



If you still have a problem after trying the above solutions, please contact CHAUVET® Technical Support.

DMX Primer

There are 512 channels in a DMX connection. A fixture capable of receiving DMX will require one or a number of sequential channels. The user must assign a starting address on the fixture that indicates the first channel reserved in the controller. There are many different types of DMX controllable fixtures and they all may vary in the total number of channels required. Choosing a start address should be planned in advance. Channels should never overlap. If they do, this will result in erratic operation of the fixtures whose starting address is set incorrectly. You can however, control multiple fixtures of the same type using the same starting address as long as the intended result is that of unison movement or operation. In other words, the fixtures will all respond exactly the same.

DMX fixtures are designed to receive data through a daisy chain. A daisy chain connection is where the DATA OUT of one fixture connects to the DATA IN of the next fixture. The order in which the fixtures are connected is not important and has no effect on how a controller communicates to each fixture. Use an order that provides for the easiest and most direct cabling. Connect fixtures using shielded two conductor twisted pair DMX data cable with three pin XLR male to female connectors. The shield connection is pin 1, while pin 2 is Data Negative (S-) and pin 3 is Data positive (S+).

Fixture Linking (Daisy Chain)

You will need a daisy chain to run light shows of one or more fixtures using a DMX controller or to run synchronized shows on two or more fixtures set to a master/slave operating mode. The combined number of channels required by all the fixtures on a daisy chain determines the number of fixtures the data link can support.



To comply with the EIA-485 standard, do not connect more than 32 fixtures on one daisy chain. Connecting more than 32 fixtures on one daisy chain without the use of a DMX optically-isolated splitter may result in deterioration of the digital DMX signal.

Maximum recommended cable distance: 500 m (1640 ft)

Maximum recommended number of fixtures on a daisy chain: 32

Data Cabling

To link fixtures together you must obtain data cables. You can purchase CHAUVET® certified DMX cables directly from a dealer/distributor or construct your own cable. If you choose to create your own cable please use data-grade cables that can carry a high quality signal and are less prone to electromagnetic interference.


DMX Data Cable

Use a Belden® 9841 or equivalent cable which meets the specifications for EIA RS-485 applications. Standard microphone cables cannot transmit DMX data reliably over long distances. The cable must have the following characteristics:

Type:	shielded, 2-conductor twisted pair
Maximum capacitance between conductors:	30 pF/ft
Maximum capacitance between conductor and shield:	55 pF/ft
Maximum resistance:	20 ohms/1000 ft
Nominal impedance:	100 ~ 140 ohms

Cable Connectors

Cabling must have a male XLR connector on one end and a female XLR connector on the other end.



Do not allow contact between the common and the fixture's chassis ground. Grounding the common can cause a ground loop, and your fixture may perform erratically. Test cables with an ohm meter to verify correct polarity and to make sure the pins are not grounded or shorted to the shield or each other.

Setting the Starting Address

This DMX mode enables the use of a universal DMX controller device. Each fixture requires a start address from 1~512. A fixture requiring one or more channels for control begins to read the data on the channel indicated by the start address. For example, a fixture that uses six DMX channels and was addressed to start on DMX channel 100, would read data from channels: 100, 101, 102, 103, 104, and 105. Choose start addresses so that the channels used do not overlap, and note the start address selected for future reference.

If this is your first time addressing a fixture using the DMX control protocol, we suggest jumping to the "Appendix" section and reading the heading "DMX Primer". It contains very useful information that will help you understand its use.

3-Pin to 5-Pin Conversion Chart




If you use a controller with a 5-pin DMX output connector, you will need to use a 5-pin to 3-pin adapter. The chart below details a proper cable conversion:

3-PIN TO 5-PIN CONVERSION CHART		
Conductor	3-Pin Female (Output)	5-Pin Male (Input)
Ground/Shield	Pin 1	Pin 1
Data (-) signal	Pin 2	Pin 2
Data (+) signal	Pin 3	Pin 3
Not used		Pin 4
Not used		Pin 5

Setting up a DMX Daisy Chain

1. Connect the (male) 3-pin connector side of the DMX cable to the output (female) 3-pin connector of the controller.
2. Connect the end of the cable coming from the controller which will have a (female) 3-pin connector to the input connector of the next fixture consisting of a (male) 3-pin connector.
3. Then, proceed to connect from the output as stated above to the input of the following fixture and so on.

Universal DMX Controller



General Maintenance

To maintain optimum performance and minimize wear, fixtures should be cleaned frequently. Usage and environment are contributing factors in determining cleaning frequency. As a general rule, fixtures should be cleaned at least twice a month. Dust build up reduces light output performance and can cause overheating. This can lead to reduction in the life of the light source and mechanical wear. Be sure to power off fixture before conducting maintenance.

- Unplug fixture from power.
- Use a vacuum or air compressor and a soft brush to remove dust collected on external vents.
- Clean all lenses when the fixture is cool with a mild solution of glass cleaner or Isopropyl Alcohol and a soft lint free cotton cloth or lens tissue.
- Apply solution to the cloth or tissue and drag dirt and grime to the outside of the lens.
- Gently polish optical surfaces until they are free of haze and lint.



Always dry the parts carefully after cleaning them.



If the fixture has one or more fans, never spin them using compressed air.

Returns Procedure

Returned merchandise must be sent prepaid and in the original packing; call tags will not be issued. Package must be clearly labeled with a Return Merchandize Authorization Number (RMA #). Products returned without the RMA # will be refused. Call CHAUVET® and request an RMA # prior to shipping the fixture. Be prepared to provide the model number, serial number and a brief description of the cause for the return. Be sure to pack fixture properly; any shipping damage resulting from inadequate packaging is the customer's responsibility. As a suggestion, proper UPS packing or double-boxing is always a safe method to use. CHAUVET® reserves the right to use its own discretion to repair or replace product(s).



If you are given an RMA #, please include the following information on a piece of paper inside the box:

- 1) ***Your name***
- 2) ***Your address***
- 3) ***Your phone number***
- 4) ***The RMA #***
- 5) ***A brief description of the symptoms***

Claims

Damage incurred in shipping is the responsibility of the shipper; therefore, the damage must be reported to the carrier upon receipt of merchandise. It is the customer's responsibility to notify and submit claims with the shipper in the event that a fixture is damaged due to shipping. Any other claim for items such as missing component/part, damage not related to shipping, and concealed damage, must be made within seven (7) days of receiving merchandise.

TECHNICAL SPECIFICATIONS

WEIGHT & DIMENSIONS

Length9.1 in (231 mm)
Width11.8 in (300 mm)
Height13 in (330 mm)
Weight8.3 lbs (3.7 kg)

POWER

Input voltage 100~240 VAC, 50/60 Hz (auto-ranging)
Power and current 27 W; 0.3 A max (120 V, 60 Hz)
Power consumption 31 W; 0.2 A max (230 V, 50 Hz)
Power linking.....max 26 units @ 120 V; 40 units @ 230 V
Fuse F 1 A, 250 V

LIGHT SOURCE

Type5 mm, LED
Quantity320 total; 80 red, 80 green, 80 blue, 40 white, 40 amber; (64 per pod)
Rating100,000 hrs

PHOTO OPTIC

Coverage angle55°

INDOOR/OUTDOOR

Rating For indoor use only

THERMAL

Maximum ambient temperature104° F (40° C)

CONTROL & PROGRAMMING

Data input.....locking 3-pin XLR male socket
Data outputlocking 3-pin XLR female socket
Data pin configuration..... pin 1 shield, pin 2 (-), pin 3 (+)
Protocols DMX-512 USITT
DMX Channels 3

ORDERING INFORMATION

Circus™ CIRCUS

WARRANTY INFORMATION

Warranty..... 2-year limited warranty

CONTACT Us

WORLD HEADQUARTERS

General Information CHAUVET®
Address 5200 NW 108th Ave
Sunrise, FL 33351
Voice 954-929-1115
Voice (toll free) 800-762-1084
Fax 954-929-5560
Technical Support CHAUVET®
Voice 954-929-1115 (Press 4)
Fax 954-929-5560 (Attention: Service)
Email tech@chauvetlighting.com
World Wide Web <http://www.chauvetlighting.com>

UNITED KINGDOM & IRELAND

General Information CHAUVET® Europe Ltd
Address Unit 1C
Brookhill Road Industrial Estate
Pinxton, Nottingham, UK
NG16 6NT
Voice +44 (0)1773 511115
Fax +44 (0)1773 511110
Email uktech@chauvetlighting.com
World Wide Web <http://www.chauvetlighting.co.uk>